



USER MANUAL



HoVR 1.0 Weather Meter (Anemometer)

TO USE

Power On:

Press the "Power" button.

Power Off:

With the unit powered on press the "Power" button.

Wind Speed:

Press the "WIND" button.

Change Wind Speed Units:

Press the "WIND" button to cycle through m/s, Km/h, ft/min, knots, MPH.

Minimum, Maximum, and Average Wind Speeds:

Press the "MODE" button to cycle through MAX, MIN, AVG wind speed modes.

Barometric Pressure:

Press the "BARO" button.

Change Barometric Pressure Units:

Press the "BARO" button to cycle through inHg and hpa mbar.

Note: 1 inHg=33.8638816 hpa mbar

Calibrate Barometric Pressure:

1. Press and hold the "ALT" button for ~5 seconds.
2. Press the "WIND" button to increase and "T/RH" button to decrease the pressure to match a calibrated barometer reading.
3. Press and hold the "ALT" button for ~5 seconds and the unit will store the updated pressure and power off.

Temperature:

Press the "T/RH" button.

Change Wind Speed Units:

Press the "T/RH" button to cycle through C and F.

Relative Humidity:

Press the "T/RH" button until "RH%" is displayed on the second row of the display.

Altitude:

Press the "ALT" button.

Change Altitude Units:

NOTE: Altitude Readings are an estimate based on barometric pressure and temperature. If pressure is below sea level you will get readings of "0".

Press the "ALT" button to cycle through FT and M.

Turn Backlight On:

Press and hold the "MODE" button for ~3 seconds.

Turn Backlight Off:

With backlight on press and hold the "MODE" button for ~3 seconds.

How to replace the battery:

- Remove battery panel cover on rear of unit
- Install two (2) AAA Alkaline batteries
- Re-install battery panel

TROUBLESHOOTING

Receiving incorrect readings:

Incorrect readings, particularly wind readings of greater than zero when the impeller is not turning is caused by extremely low battery. Replace battery and test unit.

Does not show up in HORUS Ballistics App or will not connect:

1. Bluetooth on phone turned off:
Verify in your phone settings that Bluetooth is turned on.
2. Extremely low battery:
If battery low symbol is displayed on the unit replace the battery and reconnect to the unit.
3. Signal Interference:
If frequently connecting and disconnecting multiple peripherals to your phone via Bluetooth or there is excessive interference from large numbers of cellular, Bluetooth, wi-fi, or other electrical signals in the area can interfere with the

connection between your phone and the HoVR 1.0 Weather Meter. To resolve close the HORUS Ballistics App the power off the unit, then re-open the HORUS Ballistics App and power on the unit and re-connect.

LIMITED WARRANTY (Transferable)

Congratulations on your purchase of a Horus Vision product. As provided herein, Horus Vision warrants (the "Limited Warranty") to its original purchasing customer and permitted transferees (collectively, a "Customer") that manufactured products (the "Product" or Products," as the context so requires) sold by Horus Vision will be free from defects in material or workmanship for the intended use and under normal conditions for a period of thirty-six (36) months from the date of sale of such Product to the initial Customer. Date of sale shall be established by the initial Customer's purchase receipt or by the products serial number if purchased directly from Horus Vision.

Remedies

If Customer believes that a Product is defective and covered by this Limited Warranty, Customer must notify Horus Vision in writing within 30 days of its discovery of the defect, at which time Customer will receive a Return Merchandise Authorization ("RMA") number. The Customer's notice must identify the Product, including by serial number, and contain a detailed description of the alleged defect. The method of such notification must be by

completing an RMA Request Form at www.horusvision.com or by telephone at (866) 568-2926. All returns must be accompanied by an RMA number and a purchase receipt.

Horus Vision will investigate warranty claims in good faith and with reasonable promptness. If Horus Vision determines that the Product is defective and covered by this Limited Warranty, Horus Vision will, at its option, either repair or replace the defective Product. Horus Vision may, at its option (a) send a replacement Product to Customer, (b) repair or replace Product on-site, or (c) require Customer to ship the Product to Horus Vision's authorized service facilities. This Limited Warranty does not include the cost of Customer's removal, shipment or reinstallation of Product, which shall all be at Customer's risk and expense. The foregoing are Customer's sole and exclusive remedies for any defect in any Product.

This Limited Warranty may be transferred to a transferee, provided adequate documentation can be provided to establish date of purchase to Horus Vision as set forth above.

Exclusions

This Limited Warranty does not apply to:

(a) damage caused by accident, abuse, misuse, negligence, general wear and tear, extreme temperatures, flood, fire, earthquake or other external or extraordinary causes; (b) damage caused by using or operating the Product outside the permitted or intended uses described by Horus Vision; (c) damage caused by the failure to properly install, maintain and operate the Product in accordance with Horus Vision's recommendations; (d) damage caused by service (including repairs and modifications) performed by anyone other than Horus Vision; (e) any Product that has been modified; (f) any Product that has had its serial number altered or removed; (g) the inability of Customer to use the Product; (h) cosmetic damage, including but not limited to scratches and dents; (i) any accessories such as lens caps, straps and cases; and (j) any batteries, or damage directly or indirectly caused by batteries.

Limitations

This Limited Warranty is given in lieu of all other warranties, express or implied, including, but not limited to, implied warranties of merchantability and fitness for a particular purpose. Horus Vision is not responsible for direct, indirect, special, general, incidental or consequential damages resulting from

any breach of warranty or condition, or under any other legal or equitable theory, including but not limited to loss of use; loss of revenue; loss of actual or anticipated profits (including loss of profits on contracts); loss of the use of money; loss of anticipated savings; loss of business; loss of opportunity; loss of goodwill; loss of reputation; or any other indirect or consequential loss or damage howsoever caused. Please note that some states and countries do not allow the exclusion or limitation of certain types of damages or claims, so the foregoing limitations may not apply to every Customer. In states or countries where permissible, Horus Vision limits the duration of all implied warranties to the period of this Limited Warranty.

General

This Limited Warranty grants specific legal rights. Customer may also have other rights which vary from state to state (or by country). This Limited Warranty may not be transferred by Customer, except as provided above. No person is authorized to make any modification, extension or addition to this Limited Warranty except an authorized agent of Horus Vision. If any term is held to be illegal or unenforceable, the legality or enforceability of the remaining terms shall not be affected or impaired. This Limited Warranty shall be governed by the laws of the State of Idaho, USA, without regard to

any conflict of law provisions or the United Nations Convention on Contracts for the International Sale of Goods. Horus Vision reserves the right to discontinue manufacture of any Product or change Product materials, design or specifications without notice.

WARNINGS

Equipment packaging and waste products should be handled or recycled in accordance with all applicable laws and regulations.

FCC Statement

- This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user


is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna;
 - Increase the separation between the equipment and receiver;
 - Connect the equipment into an outlet on a circuit different from that to which the receiver is connected;
 - Consult the dealer or an experienced radio/TV technician for help.
- This equipment does not contain any user-serviceable parts. The user is cautioned that changes and modifications made to the equipment without the approval of manufacturer could void the user's warranty and authority to operate this equipment under Part 15 regulations. Shielded interface cable must be used with the equipment in order to comply with the

limits for a digital device pursuant to Subpart B of Part 15 of FCC Rules.

- FCC ID: 2AQWN-HOVR

California

-  WARNING: This product contains a chemical known in the State of California to cause cancer and birth defects or other reproductive harm. For more information, visit www.P65Warnings.ca.gov.

Canada

- IC: 24245-HOVR

Disposal of Electric and Electronic Equipment

(Applicable in EU and other European countries with separate collection systems)

This equipment contains electric and/or electronic parts and must therefore not be disposed of as normal household waste. For proper treatment, recovery and recycling, please take this product(s) to designated collection points where it will be accepted free of charge. Alternatively, in some

countries, you may be able to return your products to your local retailer upon purchase of an equivalent new product.

If the equipment contains exchangeable (rechargeable) batteries, these too must be removed before and properly disposed. Further information about the subject is available at your community administration, your local waste collection company, or in the store where you purchased this equipment.



Horus Vision Reticle Technologies

Website
www.horusvision.com

Phone
(866) 568-2926

Email
info@horusvision.com

Mailing Address
Horus Vision
P.O. Box 616
Lewiston, ID 83501



<https://twitter.com/HorusVision1>

https://www.instagram.com/horus_vision

<https://www.youtube.com/user/HorusScope>